

# C2 - TR - 3000

## PROCAP BOOSTER

12V  
24V



HEAVY DUTY

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

### 20A CIRCUIT BREAKER



Model  
C2-TR-3000

Volts  
12/24

Peak Amps (A)  
18000/9000

# Of Batteries  
0

Location of Fuse  
Clamp

Fuse (A)  
500

Dimensions (cm)  
54x42x26

Cable Ø (mm2)  
50

Cable Length (cm)  
182

Unit Weight (KG)  
23

Charger Voltage (V)  
14.4

Charger Amps (A)  
3

Vehicle types



**LEMANIA ENERGY**  
Switzerland +

# C2 - TR - 3400

## PROCAP BOOSTER

12V  
24V



HEAVY DUTY

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

### 20A CIRCUIT BREAKER



Model  
C2-TR-3400

Volts  
12/24

Peak Amps (A)  
19000/9500

# Of Batteries  
0

Location of Fuse  
Clamp

Fuse (A)  
500

Dimensions (cm)  
54x42x26

Cable Ø (mm2)  
50

Cable Length (cm)  
182

Unit Weight (KG)  
23

Charger Voltage (V)  
14.4

Charger Amps (A)  
3

Vehicle types



**LEMANIAENERGY**  
Switzerland +