

# P21-ST-5000

## START BOOSTER

### INBUILT SAFETY FUSE

Pure brass clamps with braided connection protected by a safety fuse.

12V  
24V



### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.



### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



#### Model

P21-ST-5000

#### Volts

12V/24V

#### Peak Amps (A)

5000/2500

#### # Of Batteries

1

#### Location of Fuse

Clamp

#### Fuse (A)

500

#### Dimensions (cm)

41x34x24

#### Cable Ø (mm<sup>2</sup>)

50

#### Cable reach (cm)

150

#### Unit Weight (KG)

21

#### Charger Voltage (V)

14.4

#### Charger Amps (A)

3

#### Vehicle types



**LEMANIAENERGY**  
Switzerland +

# P21-ST-6400

## START BOOSTER

12V  
24V



### INBUILT SAFETY FUSE

Pure brass clamps with braided connection protected by a safety fuse.

### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



**Model**  
P21-ST-6400

**Volts**  
12V/24V

**Peak Amps (A)**  
6400/3200

**# Of Batteries**  
1

**Location of Fuse**  
Clamp

**Fuse (A)**  
500

**Dimensions (cm)**  
41x34x24

**Cable Ø (mm2)**  
50

**Cable reach (cm)**  
150

**Unit Weight (KG)**  
24

**Charger Voltage (V)**  
14.4

**Charger Amps (A)**  
3

**Vehicle types**



[www.lemania-energy.com](http://www.lemania-energy.com)

**LEMANIAENERGY**  
Switzerland

Switzerland