

P21-ST-6400

START BOOSTER

INBUILT SAFETY FUSE

Pure brass clamps with braided connection protected by a safety fuse.

12V
24V



REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



Model	P21-ST-6400
Volts	12V/24V
Peak Amps (A)	6400/3200
# Of Batteries	1
Location of Fuse	Clamp
Fuse (A)	500
Dimensions (cm)	41x34x24
Cable Ø (mm²)	50
Cable reach (cm)	150
Unit Weight (KG)	24
Charger Voltage (V)	14.4
Charger Amps (A)	3

Vehicle types



www.lemania-energy.com

LEMANIAENERGY
Switzerland +