

H2 - TR - 3000

PROCAP HYBRID START BOOSTER



12V
24V

DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



Model
H2-TR-3000

Volts
12V/24V

Peak Amps (A)
9000

Farads (F)
1700

Location of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
36x16x42

Cable Ø (mm2)
50

Cable reach (cm)
170

Unit Weight (KG)
35

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



www.lemania-energy.com

LEMANIA ENERGY
Switzerland +



H2 - TR - 1500

PROCAP HYBRID START BOOSTER



DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



Model
H2-TR-1500

Volts
12V/24V

Peak Amps (A)
13600

Farads (F)
2000

Location of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
36x16x42

Cable Ø (mm2)
50

Cable reach (cm)
170

Unit Weight (KG)
35

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicule types

