

C1-TR-3400

12V
24V



PROCAP BOOSTER

TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.

DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

INBUILT SAFETY FUSE

Pure brass clamps with braided connection protected by a safety fuse.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

ULTRACAPS INSIDE

Using the latest in capacitor technology this booster can be recharged in seconds to provide unlimited starts.

RIBBED ABS CHASSIS

Reinforced internal structure provides strength and durability making a dependable chassis.



Model
C1-TR-3400

Volts
12/24V

Peak Amps (A)
10000

Of Batteries
0

Location of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
53x43x32

Cable Ø (mm2)
50

Cable Length (cm)
220

Unit Weight (KG)
25

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



LEMANIA ENERGY
Switzerland

www.lemania-energy.com