

P1 - TR - 5000

START TRUCK

12V
24V

ACM

DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



Model
P1-TR-5000

Volts
12/24

Peak Amps (A)
5000/2500

Of Batteries
2

Localton of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
53x43x32

Cable Ø (mm2)
50

Cable Length (cm)
208

Unit Weight (KG)
30

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



www.lemania-energy.com

LEMANIAENERGY
Switzerland +