

# P1 - TR - 6400

## START TRUCK

12V  
24V

AGM

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

### TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.

### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

<b>Model</b>	P1-TR-6400
<b>Volts</b>	12/24
<b>Peak Amps (A)</b>	6400/3200
<b># Of Batteries</b>	2
<b>Location of Fuse</b>	Clamp
<b>Fuse (A)</b>	500
<b>Dimensions (cm)</b>	53x43x32
<b>Cable Ø (mm<sup>2</sup>)</b>	50
<b>Cable Length (cm)</b>	208
<b>Unit Weight (KG)</b>	37
<b>Charger Voltage (V)</b>	14,4
<b>Charger Amps (A)</b>	5
<b>Vehicle types</b>	



[www.lemania-energy.com](http://www.lemania-energy.com)



**LEMANIA ENERGY**  
Switzerland +

