

# P2 - TR - 5000

## START TRUCK

12V  
24V



### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### TROLLEY SYSTEM

Easily move the booster to where it is needed using the trolley wheels and handle.



### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

**Model**  
P2-TR-5000

**Volts**  
12/24

**Peak Amps (A)**  
5000/2500

**# Of Batteries**  
2

**Location of Fuse**  
Clamp

**Fuse (A)**  
500

**Dimensions (cm)**  
54x42x26

**Cable Ø (mm2)**  
50

**Cable Length (cm)**  
182

**Unit Weight (KG)**  
25

**Charger Voltage (V)**  
14.4

**Charger Amps (A)**  
3

**Vehicle types**



### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.



[www.lemania-energy.com](http://www.lemania-energy.com)

**LEMANIA ENERGY**  
Switzerland +