P3-TR-2000 START TRUCK



Old car



AGM

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

- TROLLEY SYSTEN

Easily move the booster to where it is needed using the trolley wheels and handle.



This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

6-12V SWITCH

Easy to use switch allows the booster to be changed from 6V to 12V.



SWISS 🔛 MADE

Model P3-TR-2000

Volts 6/12 Peak Amps (A) 2000/1000

2000/1000 # Of Batteries

2

Locaiton of Fuse Clamp

Fuse (A) 500

Dimensions (cm) 53x43x32

Cable Ø (mm2) 50

Cable Length (cm)

Unit Weight (KG) 29

Charger Voltage (V) 6-12

Charger Amps (A) 2





www.lemania-energy.com