

P13-2500

START BOOSTER

12V

AGM

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

DIGITAL VOLT METER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.



Model
P13-2500

Volts
12V

Peak Amps (A)
2500A

Of Batteries
1

Location of Fuse
Optional

Fuse (A)
Optional

Dimensions (cm)
35x30x23

Cable Ø (mm2)
25

Cable Length (cm)
165

Unit Weight (KG)
13

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



Optional on/off switch

RIBBED ABS CHASSIS
Reinforced internal structure provides strength and durability making a dependable chassis.



LEMANIA ENERGY
Switzerland +

P13-3100

START BOOSTER

12V

AGM

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

DIGITAL VOLT METER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.



Model
P13-3100

Volts
12V

Peak Amps (A)
3100

Of Batteries
1

Location of Fuse
Optional

Fuse (A)
Optional

Dimensions (cm)
35x30x23

Cable Ø (mm2)
25

Cable Length (cm)
165

Unit Weight (KG)
14

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



Optional on/off switch

RIBBED ABS CHASSIS
Reinforced internal structure provides strength and durability making a dependable chassis.



LEMANIA ENERGY
Switzerland +