

P13-ST-5000

12V
24V

AGM

START TRUCK

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

12-24V CONNECTORS

Easy to use switch allows the booster to be changed from 12V to 24V.



Model
P13-ST-5000

Volts
12/24

Peak Amps (A)
5000/2500

Of Batteries
2

Location of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
35X30X30

Cable Ø (mm2)
50

Cable Length (cm)
170

Unit Weight (KG)
19

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



www.lemania-energy.com



LEMANIA ENERGY
Switzerland