

P15 - 25000

START BOOSTER

12V

AGM

LED CHARGE INDICATOR

The test button allows users to easily check the charge level of the booster and test the alternator of a vehicle.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

ON/OFF SWITCH

This model is fitted with an easy to use on off switch for maximum safety.



Model
P15-2500

Volts
12V

Peak Amps (A)
2500A

Of Batteries
1

Location of Fuse
Clamp

Fuse (A)
500

Dimensions (cm)
38x32x24

Cable Ø (mm²)
25

Cable Length (cm)
155

Unit Weight (KG)
10.7

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



LEMANIA ENERGY
Switzerland +