

# P7-ST-6200

## START TRUCK

12V  
24V

AGM

### REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.

### DIGITAL VOLTMETER

This display allows professionals to quickly see the voltage available and to test the alternator of a vehicle.

### 12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.



**Model**  
P7-ST-6200

**Volts**  
12/24

**Peak Amps (A)**  
6200/3100

**# Of Batteries**  
2

**Location of Fuse**  
Clamp

**Fuse (A)**  
500

**Dimensions (cm)**  
51x34x25

**Cable Ø (mm2)**  
50

**Cable Length (cm)**  
145

**Unit Weight (KG)**  
25

**Charger Voltage (V)**  
14.4

**Charger Amps (A)**  
3

**Vehicle types**



[www.lemania-energy.com](http://www.lemania-energy.com)



**LEMANIA ENERGY**  
Switzerland +